



Model 441

AMPLIFIER REPLACEMENT PARTS LIST
(L and R denote Left and Right Channel)

Item	Description	Part No.	Item	Description	Part No.
B1	Lite Bulb	ST-9626	CR8	600 PRV Silicon Rectifier	44875
C1 L&R	.068 mfd 200V. Capacitor	41507	CR9	600 PRV Silicon Rectifier	44875
C2 L&R	.0018 mfd 200V. Capacitor	45307	CRA1	CA 3019 Diode Array	45299
C3 L&R	.0012 mfd 200V. Capacitor	45312	F1	2 Amp 250V. Slo-Blo Fuse	ST-9600
C4 L&R	150 mmfd 1,000V. Capacitor	33438	J1	3 Pin Socket	44927
- C5 L&R	8 mfd 4V. Capacitor	45276	J2	6 Prong Min. Socket	18634
C6 L&R	.0012 mfd 200V Capacitor	45312	J3	Relay Socket	44806
- C7 L&R	200 mfd 10V. Capacitor	43538	J4	7 Circuit Combo Plug Socket	44810
- C8 L&R	200 mfd 10V. Capacitor	43538	J5	12 Cir. Mtr. Mtg. Pin Hsg. (Red)	V-7044
C9 L&R	.025 mfd 200V. Capacitor	43526	J6	6 Cir. M-N-L Soc. Hsg. (Red)	V-7007
- C10 L&R	32 mfd 64V. Capacitor	45313	J7	15 Cir. M-N-L Soc. Hsg. (White)	V-8760
C11 L&R	.47 mfd 100V. Capacitor	43535	J8	6 Cir. M-N-L Soc. Hsg. (White)	V-7005
- C12	32 mfd 64V. Capacitor	45313	J9	3 Cir. M-N-L Soc. Hsg. (White)	V-7047
C13 L&R	.15 mfd 200V. Capacitor	39472-1	K1	Mute Relay 24 V.D.C.	43561
C14 L&R	.1 mfd 200V. Capacitor	45200	M1	Vol. Cont. Mtr. Assem.	44864-A
C15 L&R	.15 mfd 200V. Capacitor	39472-1	P1	Dual Input Cable Assem.	44926-A
C16 L&R	.018 mfd 200V. Capacitor	45326	P2	6 Pin Molded Plug & Cable	44773
C17 L&R	.047 mfd 200V. Capacitor	45162	P3	Not Used	
- C18	20 mfd 450V. Capacitor	45284	P4	7 Cir. Combo Cap Hsg.	44811
- C19	100+20 mfd 475V. Capacitor	42855	P5	12 Cir. Mtr. Mtg. Soc. Hsg. (Red)	V-7045
- C20	160 mfd 25V. Capacitor	42955	P6	6 Cir. M-N-L Pin Hsg. (Red)	V-7006
C21	.15 mfd 600V. Capacitor	45199	P7	15 Cir. M-N-L Pin Hsg. (White)	V-8764
C22 L&R	3.3 P.F. 1000V. Capacitor	45279	P8	6 Cir. M-N-L Pin Hsg. (White)	V-7004
C23 L&R	330 mmfd 1000V. Capacitor	33088	P9	3 Cir. M-N-L Pin Hsg. (White)	V-7046
- C24 L&R	4 mfd 450V. Capacitor	45283	Q1 L&R	2N3391A Transistor	43565
C25 L&R	.047 mfd 600V. Capacitor	35371	Q2 L&R	2N3417 Transistor	43548
C26 L&R	.047 mfd 600V. Capacitor	35371	Q3 L&R	2N4249 Transistor	45298
- C27	250 mfd 64V. Capacitor	43536	Note: All Resistors are 1/2 W. ± 5% tolerance unless otherwise noted.		
C28	.022 mfd 200 V. Capacitor	41334	R1 L&R	270,000 ohm Lo-Noise	45291
C29	.022 mfd 200V. Capacitor	41334	R2 L&R	82,000 ohm Lo-Noise	38679
C30	9 mfd 60V. RMS non-polarized Capacitor	44762	R3 L&R	1,500 ohm Lo-Noise	41155
C31 L&R	15 mfd 35V. RMS non-polarized Capacitor	40288	R4 L&R	47,000 ohm Lo-Noise	45295
CB1	1 Amp Circuit Breaker	44782	R5 L&R	56,000 ohm Lo-Noise	45292
CPU1	Ceramic Pick-up Cartridge	35122	R6 L&R	120 ohm Lo-Noise	45293
CR1	1N4174B 1W. Zener Diode	44788	R7 L&R	82,000 ohm Lo-Noise	38679
CR2	600 PRV Plastic Sil. Rect.	44875	R8 L&R	10,000 ohm Lo-Noise	45294
CR3	800 PRV Silicon Rectifier	42942	R9 L&R	27,000 ohm Lo-Noise	43568
CR4	800 PRV Silicon Rectifier	42942	R10 L&R	Not Used	
CR5	800 PRV Silicon Rectifier	42942	R11 L&R	4,000 ohm Min P.C. Control	45311
CR6	800 PRV Silicon Rectifier	42942			
CR7	600 PRV Silicon Rectifier	44875			